

LV-7325/7320 RS232C Command List

1. Control Command

Command		Function	Note
ASCII	HEX		
C00	43h 30h 30h	Power ON	
C01	43h 30h 31h	Force Power OFF	Executes Power Off twice.
C02	43h 30h 32h	Power OFF	Normal "Power Off?"
C05	43h 30h 35h	Computer mode	
C06	43h 30h 36h	MCI mode	LV-7325 Only
C07	43h 30h 37h	Video mode	
C09	43h 30h 39h	Volume +	
C0A	43h 30h 41h	Volume -	
C0B	43h 30h 42h	Audio mute ON	
C0C	43h 30h 43h	Audio mute OFF	
C0D	43h 30h 44h	Video mute ON	same as "NO SHOW"
C0E	43h 30h 45h	Video mute OFF	same as "NO SHOW"
C0F	43h 30h 46h	Regular video image (4:3)	only under video mode
C10	43h 31h 30h	Wide video image (16:9)	only under video mode
C1C	43h 31h 43h	Menu ON	
C1D	43h 31h 44h	Menu OFF	
C1E	43h 31h 45h	Display clear	same as "CLEAR" under the MENU bar
C1F	43h 31h 46h	Normal	same as "NORMAL" key on button SW
C20	43h 32h 30h	Brightness up	
C21	43h 32h 31h	Brightness down	
C30	43h 33h 30h	D.Zoom +	
C31	43h 33h 31h	D.Zoom -	
C3A	43h 33h 41h	Pointer right	
C3B	43h 33h 42h	Pointer left	
C3C	43h 33h 43h	Pointer up	
C3D	43h 33h 44h	Pointer down	
C3E	43h 33h 45h	Right click	same as "RIGHT CLICK" on Remote
C3F	43h 33h 46h	Select	SELECT on body / LCLICK on Remote
C43	43h 34h 33h	Freeze ON	
C44	43h 34h 34h	Freeze OFF	
C46	43h 34h 36h	Zoom down	
C47	43h 34h 37h	Zoom up	
C4A	43h 34h 41h	Focus down	
C4B	43h 34h 42h	Focus up	
C59	43h 35h 39h	Page up	for MCI mode, LV-7325 Only
C5A	43h 35h 41h	Page down	for MCI mode, LV-7325 Only
C80	43h 38h 30h	Zoom mode	
C87	43h 38h 37h	Focus mode	
C88	43h 38h 38h	Digital zoom	
C89	43h 38h 39h	Auto Image	
C8E	43h 38h 45h	Keystone +	
C8F	43h 38h 46h	Keystone -	

2. Status Read Command

Command		Function	Note
ASCII	HEX		
CR0	43h 52h 30h	Power Status Read	2 Bytes
CR1	43h 52h 31h	Input mode Read	1 Byte
CR3	43h 52h 33h	Lamp time Read	4 Bytes
CR4	43h 52h 34h	Setting Read	2 Bytes

2-1. Power Status Read

Read Command		Status	Note
ASCII	HEX		
00 ACK	30h 30h 06h	Power ON	
80 ACK	38h 30h 06h	Stand by	
40 ACK	34h 30h 06h	Count down	in 30 sec. Warmup after POWER ON
20 ACK	32h 30h 06h	Cooling down	in 1 min. cool down after POWER OFF
10 ACK	31h 30h 06h	Power abnormality	
88 ACK	38h 38h 06h	Temperature abnormality	during stand-by mode
28 ACK	32h 38h 06h	Temperature abnormality	during cooling term
02 ACK	30h 32h 06h	Key input prohibition	

2-2. Input mode Read

Read Command		Status	Note
ASCII	HEX		
1 ACK	31h 06h	Computer	
2 ACK	32h 06h	MCI	LV-7325 Only
3 ACK	33h 06h	Video	

2-3. Lamp time

Read Command	Status	Note
**** ACK	4 digit 06h	cumulative

2-4. Setting

Read Command		Status	Note
ASCII	HEX		
11 ACK	31h 31h 06h	Normally	
10 ACK	31h 30h 06h	Top & Bottom reversal	
01 ACK	30h 31h 06h	Left & Right reversal	
00 ACK	30h 30h 06h	Top & Bottom/Left & Right	